

CAN Wiring Notes

The Wire between the 100 Ohm resistors should be twisted when using 22# Tefzel wire. Can devices should not be more than 500mm away from the main CAN Bus. The maximum length of the CAN Bus is 16 meters including the MoTeC CAN Cable (PC to CAN adaptor)

ADL Setup

The ADL must have hex version 2.10F in it to use the BR2 can template.

In dash Manager

- 1. Select "Inputs" then "Communications" from the menu
- 2. Click on "CAN 1" and then click on the "Select" button
- 3. Choose "BR2" from the list and then click on "OK" Button
- 4. Click on the "OK" button again
- 5. Select "Calculations" then "Lap Time and Number" from the menu
- 6. Set the "Beacon Type" value to BR2
- 7. Set the "Mode" and "ID" values to the TR Beacon Mode and ID values you are using



